



SafeSign Identity Client Minidriver Version 3.7

Release Document for Windows



Table of Contents

Warning Notice.....	III
Document Information.....	IV
About the Product	V
1 About this Document	1
2 Release Information	2
2.1 Deliverables	2
2.2 Date of Release	2
2.3 Release Details.....	2
2.4 Windows 64-bit.....	3
2.5 Release Documents.....	3
3 Features.....	4
3.1 Multiple Token Support	4
3.2 Multiple Smart Card Reader Support	4
3.3 Multiple Application Support	4
3.4 Multiple Languages Support.....	5
3.5 Activate QSCD Card Support	5
4 New Features and Fixes.....	6
4.1 New	6
4.2 Fixed	6
4.2.1 Version 3.7.1.0.....	7
5 Known Issues	8
5.1 General	8
5.2 SafeSign IC	8
6 Supported Operating Systems.....	10
7 Supported Tokens	11
7.1 Supported ATRs	12
8 Supported Smart Card Readers.....	14
9 Supported Applications	15
9.1 Token Administration Utility	15
9.2 Mozilla Firefox.....	16
9.3 Mozilla Thunderbird.....	16
9.4 Internet Explorer.....	16
9.5 Microsoft Edge.....	16
9.6 Microsoft Outlook.....	16
9.7 Adobe Reader DC.....	16
9.8 Microsoft Word.....	16
9.9 LibreOffice	17
9.10 Windows Smart Card Logon	17
9.11 Terminal Server Logon	17
10 Supported Languages.....	18
10.1 Installation language files and codes.....	19



Warning Notice

All information herein is either public information or is the property of and owned solely by A.E.T. Europe B.V. who shall have and keep the sole right to file patent applications or any other kind of intellectual property protection in connection with such information.

This information is subject to change as A.E.T. Europe B.V. reserves the right, without notice, to make changes to its products, as progress in engineering or manufacturing methods or circumstances warrant.

Installation and use of A.E.T. Europe B.V. products are subject to your acceptance of the terms and conditions set out in the license Agreement that accompanies each product. Nothing herein shall be construed as implying or granting to you any rights, by license, grant or otherwise, under any intellectual and/ or industrial property rights of or concerning any of A.E.T. Europe B.V. information.

Cryptographic products are subject to export and import restrictions. You are required to obtain the appropriate government licenses prior to shipping this Product.

The information contained in this document is provided "AS IS" without any warranty of any kind. Unless otherwise expressly agreed in writing, A.E.T. Europe B.V. makes no warranty as to the value or accuracy of information contained herein. The document could include technical inaccuracies or typographical errors. Changes are periodically added to the information herein. Furthermore, A.E.T. Europe B.V. reserves the right to make any change or improvement in the specifications data, information, and the like described herein, at any time.

A.E.T. EUROPE B.V. HEREBY DISCLAIMS ALL WARRANTIES AND CONDITIONS WITH REGARD TO THE INFORMATION CONTAINED HEREIN, INCLUDING ALL IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, TITLE AND NON-INFRINGEMENT. IN NO EVENT SHALL A.E.T. EUROPE B.V. BE LIABLE, WHETHER IN CONTRACT, TORT OR OTHERWISE, FOR ANY INDIRECT, SPECIAL OR CONSEQUENTIAL DAMAGES OR ANY DAMAGES WHATSOEVER INCLUDING BUT NOT LIMITED TO DAMAGES RESULTING FROM LOSS OF USE, DATA, PROFITS, REVENUES, OR CUSTOMERS, ARISING OUT OF OR IN CONNECTION WITH THE USE OR PERFORMANCE OF INFORMATION CONTAINED IN THIS DOCUMENT.

© Copyright A.E.T. Europe B.V., 2000-2021. All rights reserved.

SafeSign IC is a trademark of A.E.T. Europe B.V. All A.E.T. Europe B.V. product names are trademarks of A.E.T. Europe B.V. All other product and company names are trademarks or registered trademarks of their respective owners.

Credit Information:

"This product includes cryptographic software written by Eric A. Young (eay@cryptsoft.com)."

"This product includes software written by Tim J. Hudson (tjh@cryptsoft.com)."



Document Information

Document ID: SafeSign IC Minidriver Version 3.7 Release Document for Windows

Project Information: SafeSign IC Release Documentation

Document revision history:

Version	Date	Author	Changes
1.0	21 September 2021	Drs C.M. van Houten	First version for SafeSign IC Minidriver version 3.7 for Windows; release 3.7.0.0
1.1	16 December 2021	Drs C.M. van Houten	First version for SafeSign IC Minidriver version 3.7 for Windows; release 3.7.1.0

Document Approval

Version	Date	Name	Function
1.0	21 September 2021	B. Smid MBT	Chief Development Officer
1.1	16 december 2021	B. Smid MBT	Chief Development Officer

WE RESERVE THE RIGHT TO CHANGE SPECIFICATIONS WITHOUT NOTICE



About the Product

This competent all-rounder in terms of strong authentication, integration and compatibility gives you complete freedom and flexibility. Once rolled out, SafeSign Identity Client (IC) serves as the perfect guard for IT security and enables unlimited possibilities for securing your IT infrastructure.

SafeSign IC offers the most comprehensive support available on the market for (card) operating systems, smart cards, USB tokens, languages and functions. This means you have sustainable and permanent freedom of choice when it comes to manufacturer independence.

SafeSign IC enforces two- or multi factor authentication/logon to the network, client PC or application, requiring the end user to have both the USB token or smart card (something you have) and a Personal Identity Number (something you know). USB tokens and smart cards are physically and logically tamper-resistant, ensuring that the end user's digital credentials can not be copied, modified or shared. Authentication based on smart cards or USB tokens provides the highest degree of security.

SafeSign IC is available for both fixed and mobile devices like desktops, servers, laptops, tablets and smart phones. SafeSign IC is also found in Thin Clients, printers or any other devices requiring authentication.



1 About this Document

The aim of this document is to document the status of the release of SafeSign Identity Client Minidriver version 3.7 for Windows (henceforth referred to as “SafeSign IC Minidriver version 3.7”). This document is part of the release documentation of SafeSign IC and is intended to be a reference to both end users and administrators.



2 Release Information

2.1 Deliverables

SafeSign IC Minidriver version 3.7 is provided as an .msi installation file.

The InstallShield Wizard will guide you through the installation of SafeSign IC Minidriver version 3.7.

Alternatively, the .msi installation package can be used for centralised distribution and installation within an enterprise context.

SafeSign IC Minidriver version 3.7 includes the Token Administration Utility user interface for local smart card operations, such as Change PIN.

2.2 Date of Release

The date of the release is 16 December 2021.

2.3 Release Details

SafeSign IC Minidriver version 3.7 reflects the SafeSign IC product version numbering scheme, i.e. version number, build number and distribution number, which is reflected in the Version Information dialog of the Token Administration Utility.

- Note that the file versions of the components delivered with the release of SafeSign IC Minidriver version 3.7.1.0 do not necessarily have the name format '3.7.1.xxxx'.

Release version: Minidriver Release 3.7.1.0-AET.000		
Description	File Name	File Version
Certificate Expiration Check Utility	aetcrss1.exe	3.7.11.14
Common Dialogs	aetdls1.dll	3.7.14.1
Java Card Handling Library	aetjcss1.dll	3.9.2.1
PKCS #11 Cryptoki Library	aetpkss1.dll	3.8.5.1
PKCS #11 Library Wrapper with automatic login	aetpkssw.dll	3.7.9.33
Task Manager	aettask.dll	3.9.15.28
Secure Messaging Library	aetsm1.dll	3.9.10.19
Kit Library	aetkit1.dll	4.1.5.1
Read-write card-module	aetrwcm1x.dll (64-bit) aetrwcm1.dll (32-bit)	3.6.1.1
Token Administration Utility	tokenadmin.exe	3.8.26.1

- Note that in the distribution number (AET.000), the prefix AET is unique and reserved for AET general releases only.



- Note that when saving the version information to a file, there may be components listed that are not available in the SafeSign IC version installed. For example, in SafeSign IC Minidriver version 3.7, the Credential Provider 'aetcpss1.dll' is listed, but as 'not installed'.

2.4 Windows 64-bit

SafeSign IC Minidriver version 3.7 comes in a 64-bit version only (which does not install on 32-bit Windows Operating Systems) that will work with both 32-bit and 64-bit applications.

- Note that there are two system directories on Windows 64-bit Operating Systems: System32, which is reserved for 64-bit applications and SysWOW64, which is reserved for 32-bit applications.

SafeSign IC Minidriver version 3.7 system files will install in both directories (to ensure that both 32-bit and 64-bit applications can work with SafeSign IC), with the following exceptions, which are installed in the System32 directory only:

- The Certificate Expiration Check Utility (aetcrss1.exe);
- The Task Manager (aettask.dll).

The Token Administration Utility's Version Information dialog will indicate which installed files have a 32-bit and/or a 64-bit file version.

2.5 Release Documents

SafeSign IC Minidriver version 3.7 provides at least the following release documentation:

Document Name	Version
SafeSign IC Minidriver Version 3.7 Release Document for Windows	1.1



3 Features

The following features are supported by SafeSign IC Minidriver version 3.7:

- 1 Multiple Token Support
- 2 Multiple Smart Card Reader Support
- 3 Multiple Application Support
- 4 Multiple Language Support
- 5 Activate QSCD Card Support

These features are described in the following paragraphs.

3.1 Multiple Token Support

SafeSign IC Minidriver version 3.7 supports a large number of smart cards and tokens, as listed in section 7.

Newly supported smart card and tokens in SafeSign IC Minidriver version 3.7 are:

- JCOP 4 P71:
 - Note that JCOP 4 P71 chip modules / cards are not available yet, but that preparations have been made in SafeSign IC Minidriver version 3.7 to enable the use of JCOP 4 as QSCD card or UZI-pas 4 (by including model IDs, ATR and activation profiles).

3.2 Multiple Smart Card Reader Support

SafeSign IC Minidriver version 3.7 supports the use of PCSC 2.0 Class 1 smart card readers.

Note that a correct operation of a smart card reader depends on correctly working reader drivers.

SafeSign IC Minidriver version 3.7 has been tested to support a number of smart card readers, as listed in section 8.

3.3 Multiple Application Support

SafeSign IC Minidriver version 3.7 supports applications on Windows that work through PKCS #11 or Microsoft CryptoAPI (NG).

SafeSign IC Minidriver version 3.7 supports a number of applications, that provide the following functionality:

- Web authentication
- Email signing and encryption
- Document signing
- Smart card logon
- Terminal Server logon

SafeSign IC Minidriver version 3.7 has been tested to support a number of applications, as listed in section 9.



3.4 Multiple Languages Support

SafeSign IC Minidriver version 3.7 supports a number of different languages.

When installing the SafeSign IC Minidriver .msi package, the default language of the installation program will be English. In order to install the .msi in a particular language, you will need to install the .msi with specific parameters, to apply a transform.

Section 10.1 lists the Windows language code identifiers and transform files to do so.

3.5 Activate QSCD Card Support

In accordance with the (European) eIDAS Regulation and related standards for cryptographic modules, the legitimate user / signatory of a Qualified Signature Creation Device (QSCD) is responsible for activating the card (keys), i.e. to change the state of the card (keys) from non-operational to operational.

The SafeSign IC Token Administration Utility offers users of a QSCD the possibility to activate their card. When a QSCD is inserted in the smart card reader, the SafeSign IC middleware will enable the user to activate the card, based on the presence of the Common Criteria (CC) certified SafeSign IC applet and the card specific ATR. If these conditions are met, the Token menu of the SafeSign IC Token Administration Utility will display the option 'Activate Card'.

- Note that the activation process for a particular card may be very specific. It may require the user to:
 - authenticate to the card by entering the PIN (UZI-pas 3, SafeSign QSCD);
 - change the Transport PIN set for the card (Defensiepas 3);

SafeSign IC Minidriver version 3.7 supports the following QSCD cards:

- Defensiepas 3¹
- UZI-pas 3²
- SafeSign Default / Generic QSCD (JCOP 3)
- UZI-pas 4
- QSCD on JCOP 4

¹ Defensiepas 3 is supported from SafeSign IC Minidriver version 3.5.4.0 onwards.

² UZI-pas 3 is supported from SafeSign IC Minidriver version 3.5.6.1 onwards.



4 New Features and Fixes

SafeSign IC Minidriver version 3.7 has a number of new features and fixes / changes.

Section 4.1 will describe the new features and functionality.

Section 4.2 will describe the improved and fixed features and functionality.

4.1 New

- Added (preparatory) support for the QSCD on JCOP 4 P71 (ATR) on NXP JCOP 4 P71.
- Added (preparatory) support for UZI-pas 4 (ATR) on NXP JCOP 4 P71.
- SafeSign IC now uses Windows Installer XML (WiX).

4.2 Fixed

- On Windows 10, the locale settings “Serbian (Cyrillic, Serbia)” and “Serbian (Latin, Serbia)” were not working. Microsoft changed handling of the Serbian language on Windows 10, which causes wxwidgets to not recognize the language (language unknown). This has been fixed in in SafeSign IC Minidriver version 3.7 with a new version of wxwidgets.
- As of Mozilla Firefox version 90, Firefox will automatically find and offer to use client authentication certificates provided by the operating system on Windows. See: <https://blog.mozilla.org/security/2021/07/28/making-client-certificates-available-by-default-in-firefox-90/>. Because it is no longer necessary to install the SafeSign IC PKCS #11 Library as a security module in Firefox, the Firefox Installer has been removed from installation process of SafeSign IC Minidriver version 3.7.
- There were problems in an application called PJeOffice when using the SafeSign IC PKCS #11 Library. Users would experience a Device Error reported by the Sun PKCS #11 wrapper. The error was caused by the fact that PJeOffice still uses MD5. In SafeSign IC Minidriver version 3.7, MD5 will no longer be listed as an available mechanism, causing PJeOffice to fallback to another algorithm (supported by the card).
- The ‘StarSign Crypto USB Token S NR’, ‘StarSign Crypto USB Token S Std’ and ‘StarSign Crypto USB Token S StdR’ used in Brazil are renamed to ‘G&D Sm@rtCafe Expert 7.0 NR’, ‘G&D Sm@rtCafe Expert 7.0 Std’ and ‘G&D Sm@rtCafe Expert 7.0 StdR’. Note that the ‘StarSign Crypto USB Token S’ (with non-RIC applet) is not renamed.
- The “Empty” key for SafeSign Default QSCD (JCOP 3) is renamed to “GenericQSCD”.
- Support for the Gemalto IDCore 30 (ATR) is re-introduced.



4.2.1 Version 3.7.1.0

- When saving the version information from the Token Administration Utility to a file on Windows 11, Windows Server 2019 and Windows Server 2022, the resulting file will display it is a Windows 10 Operating System. This is caused by Microsoft not returning this information through its usual Windows API calls. In SafeSign IC Minidriver version 3.7.1.0, we have therefore added the *CurrentBuildNumber*. This will result for example in the following notation for Windows 11: 'Windows 10 Professional, 64-bit (Windows 10 Enterprise Client 21H2 22000)'. You can then lookup the build number '22000' in: https://en.wikipedia.org/wiki/List_of_Microsoft_Windows_versions.
- There was an issue in SafeSign IC Minidriver version 3.7.0.0, where the Key Generation Notification that appears when the SafeSign IC PKCS #11 Library is used for generating keys, is empty and has to be closed after the enrollment. In SafeSign IC Minidriver version 3.7.1.0, the built-in Key Generation Notification has now been removed from the Task Manager, so it will no longer be displayed.



5 Known Issues

5.1 General

- When installing the SafeSign IC Minidriver .msi package, the default language of the installation program will be English. In order to install the .msi in a particular language, you will need to install the .msi with specific parameters, to apply a transform.
- Firefox cannot handle a certificate that does not have a label. As a workaround, you can set a label on the keys and certificate in the Token Administration Utility's Show Token Objects dialog.
- As of Mozilla FireFox version 90, Firefox will automatically find and offer to use client authentication certificates provided by the operating system on Windows. See: <https://blog.mozilla.org/security/2021/07/28/making-client-certificates-available-by-default-in-firefox-90/>. As a consequence, it is no longer necessary to install the SafeSign IC PKCS #11 Library as a security module in Firefox.
- There is an error in Thunderbird version 91 where decrypting encrypted messages fails. This is an error triggered when using the 'OS Client Cert Module' library. The decrypt functions all return CKR_FUNCTION_NOT_SUPPORTED (see https://bugzilla.mozilla.org/show_bug.cgi?id=1728519). Until Thunderbird fixes the issue, the workarounds are 1) to disable security.osclientcerts.autoload in the registry ([HKEY_LOCAL_MACHINE\SOFTWARE\WOW6432Node\Policies\Mozilla\Thunderbird\Preferences]), so the S/MIME module is not loaded and used upon start of Thunderbird or 2) to install the SafeSign PKCS#11 library as S/MIME security module.

5.2 SafeSign IC

- When generating / importing a Digital ID file or certificate and the message that the token is full (out of memory: 0x80090023) is displayed, it may be that the whole or parts of the Digital ID file (and certificate chain) or the certificate have been placed on the smart card nevertheless. This will be clearly visible in the Token Administration Utility (Show Token Objects).
- When initialising or wiping a token with Root CA certificates, you can only select a particular directory. It is not possible to select a particular file.
- When importing a CA certificate file (either during initialisation or by the function Import Certificate), *.crt files are not selected by the default file extensions (*.cer, *.der), although the import does work.
- Cards that do not support logical channels do not support challenge response authentication (unlock).
- When creating a data object containing no data (done by using an empty CKA_VALUE), an error occurs (CKR_DEVICE_ERROR). According to the PKCS #11 standard, it is allowed to leave the CKA_VALUE empty. Although the SafeSign PKCS #11 implementation correctly handles the empty CKA_VALUE, the command to create the file fails. As a workaround, a null-byte should be used instead of an empty byte.



- It is not possible to enrol a 1024 bits key pair on a RIC Card, as this is not supported (it is possible to generate a 2048 bits key pair).
- The Token Utility will only display and register Digital IDs that have a private key. When requesting a new Digital ID, the Token Utility will not display the new Digital ID with the green card icon. This is caused by the fact that the Minidriver does not update the token cache. This is a display issue only (the keys and certificates are stored on the token) and it does not affect the functionality of the SafeSign IC Minidriver / the Digital ID in any way.
- When requesting a keypair and certificate through Microsoft AD Certificate Services in Internet Explorer, selecting SHA256 or higher as the signing algorithm, you will be asked for your PIN twice. This is caused by both the Microsoft Base Smart Card CSP and KSP being used by Microsoft and requesting the PIN.
- Starting from Windows 8, the way smart cards are handled, has changed. Most notably, if a transaction is started and no activity happens for 5 seconds, the transaction (and card) are automatically reset. This has consequences for enrolling a certificate with Microsoft FIM / MIM using the Microsoft Base Smart Card CSP (see the SafeSign IC Administrator's Guide) and and for T=0 cards (see known issue below).
- The support for the non-standard <keygen> HTML element and HTMLKeygenElement DOM interface has been removed with Firefox 69. This means that any enrolment that uses the browser to generate the key pair will cease to work with Firefox 69 onwards. Please refer to: <https://developer.mozilla.org/en-US/docs/Web/HTML/Element/keygen>.
- On Windows 8 and higher, when enrolling for a key pair and certificate through the Microsoft AD Certificate Services in Internet Explorer, the Certificate Enrollment Control (certenrollctrl.exe) is not unloaded / terminated when Internet Explorer is closed (and the context is kept open). This results in a situation that when the token is wiped in between enrollments, the token contains both the previous Digital ID (before the wipe) and the new Digital ID (requested after the wipe). However, you will not be able to use the previous Digital ID.
- On Windows 8 and higher, when using a T=0 card, entering an incorrect PIN code in Internet Explorer secure web authentication, gives an error: "The smart card does not support this operation". This is caused by the card being reset (as a result of changes from Windows 8 in the way smart cards are handled). Though this happens with T=1 cards as well, it seems that Microsoft has bad recovery for T=0 cards in this case. As a workaround, you can enable the 'KeepAlive' registry setting (to prevent the transaction from timing out) or to remove and re-insert the card when it happens.
- In languages other than English, some items in the Version Information dialog are not translated (e.g. Build number, Distribution number and the names of the Secure Messaging libraries).
- When enabling the registry setting GenerateEventLogs (in HKEY_LOCAL_MACHINE\SOFTWARE\WOW6432Node\A.E.T. Europe B.V.\SafeSign\2.0), events will be logged (such as incorrect PIN attempts), but also an error (EventID 258) will occur. This has been the case in previous SafeSign IC Minidriver versions as well.
- In SafeSign IC Minidriver version 3.7, the Certificate Expiration Warning dialog will not appear by default every time a token is inserted (without the Token Administration Utility open). This will be fixed in a future release.



6 Supported Operating Systems

SafeSign IC Minidriver version 3.7 has been tested to support the following x64 Windows Operating System(s):

Operating System	Version 3.6.0.0	Version 3.7.0.0	Version 3.7.1.0
Windows 8.1 (Enterprise)	√	√	√
Windows 10 (Professional, Enterprise)	√	√	√
Windows 11 (Pro, Enterprise)			√
Windows Server 2016	√	√	√
Windows Server 2019	√	√	√
Windows Server 2022			√

Like every SafeSign IC release, SafeSign IC Minidriver version 3.7 was tested on the abovementioned Windows Operating Systems with the (latest) Service Pack and Updates available at that time. Though SafeSign IC Minidriver version 3.7 may work on older / other versions of these Operating Systems, only support requests for issues reproduced on the supported Windows Operating Systems listed above (up-to-date with the latest Windows Updates) will be taken into consideration.



7 Supported Tokens

SafeSign IC Minidriver version 3.7 supports a number of smart cards and tokens, as listed below. These tokens have been tested to work as part of the release testing for SafeSign IC Minidriver version 3.7.

The SafeSign IC PKI applet enables end users to utilise Java Card 2.2.2 and higher compliant cards with the SafeSign IC middleware. A Java card or token must contain an installed SafeSign IC applet before it can be used with SafeSign IC.

As the correct functioning of SafeSign IC is depending on a properly produced smart card or USB Token, AET requires that smart cards and / or USB tokens are produced for use with SafeSign IC in accordance with our QA policies (which require i.a. the correct applet to be pre-installed in a secure environment and a custom keyset). This is a condition to be eligible for support by AET in case of problems, in addition to the purchase / existence of a valid SafeSign IC Support Agreement.

Card Type
Defensiepas 2
Defensiepas 3 (QSCD)
G&D Sm@rtCafé Expert 3.2
G&D Sm@rtCafé Expert 4.0
G&D Sm@rtCafé Expert 5.0
G&D Sm@rtCafé Expert 6.0
G&D Sm@rtCafé Expert 7.0
Gemalto IDCore 30
Infineon Oracle JCOS Ed.1
JCOP21 v2.3
NXP J2A080 / J2A081 (JCOP 2.4.1 R3)
NXP J2D081 (JCOP 2.4.2 R2)
NXP J3A080 (JCOP 2.4.1 R3)
NXP JCOP 2.4.2 R3
NXP JCOP 3 SecID P60
NXP JCOP 4 P71



Card Type
Oberthur IDone Cosmo v7.0
RDW ABR kaart
Rijkspas
Rijkspas 2
StarSign Crypto USB Token S
UZI-pas 2
UZI-pas 3 (QSCD)
UZI-pas 4 (QSCD)

7.1 Supported ATRs

Below you will find a complete list of the ATRs supported by SafeSign IC Minidriver version 3.6.

Card Name	ATR
Defensiepas 2	3b,f9,18,00,00,81,31,fe,45,39,35,32,38,35,30,31,33,32,d9
Defensiepas 3	3b,dc,18,ff,81,91,fe,1f,c3,06,0a,2b,06,01,04,01,e9,10,05,01,03,d2
G&D Sm@rtCafe Expert 3.2 (T=CL) DSV	3b,7a,18,00,00,73,66,74,65,20,63,64,31,34,34
G&D Sm@rtCafe Expert 3.2 72k	3b,f7,18,00,00,80,31,fe,45,73,66,74,65,2d,6e,66,c4
G&D Sm@rtCafe Expert 3.2 80k	3b,fd,18,00,00,80,31,fe,45,73,66,74,65,2d,63,64,30,38,30,2d,6e,66,dc
G&D Sm@rtCafe Expert 3.2 FI	3b,fd,18,00,00,80,31,fe,45,73,66,74,65,20,63,64,31,34,34,2d,6e,66,d8
G&D Sm@rtCafe Expert 3.2 FI (T=CL)	3b,8d,80,01,73,66,74,65,20,63,64,31,34,34,2d,6e,66,3b
G&D Sm@rtCafe Expert 4.0	3b,78,13,00,00,00,73,c8,40,13,00,90,00
G&D Sm@rtCafe Expert 4.0 FI	3b,f8,18,00,00,80,31,fe,45,00,73,c8,40,13,00,90,00,92
G&D Sm@rtCafe Expert 4.0 FI (T=CL)	3b,88,80,01,00,73,c8,40,13,00,90,00,71
G&D Sm@rtCafe Expert 5.0 (T=CL)	3b,89,80,01,53,46,2d,34,43,43,2d,30,31,28
G&D Sm@rtCafe Expert 6.0 (USB Token)	3b,fd,18,00,00,81,31,fe,45,53,43,45,36,30,2d,43,43,30,38,31,2d,46,c2
G&D Sm@rtCafe Expert 6.0 FIPS	3b,fd,18,00,00,80,31,fe,45,53,43,45,36,30,2d,43,44,30,38,31,2d,46,c4
G&D Sm@rtCafe Expert 6.0 FIPS (T=CL)	3b,8d,80,01,53,43,45,36,30,2d,43,44,30,38,31,2d,46,27
G&D Sm@rtCafe Expert 6.0 FIPS 144k (T=CL)	3b,8d,80,01,53,43,45,36,30,2d,43,44,31,34,35,2d,46,2e
G&D Sm@rtCafe Expert 6.0 Non FIPS	3b,fe,18,00,00,80,31,fe,45,53,43,45,36,30,2d,43,44,30,38,31,2d,6e,46,a9
G&D Sm@rtCafe Expert 6.0 Non FIPS (T=CL)	3b,8e,80,01,53,43,45,36,30,2d,43,44,30,38,31,2d,6e,46,4a
G&D Sm@rtCafe Expert 6.0 Non FIPS 144k	3b,fe,18,00,00,80,31,fe,45,53,43,45,36,30,2d,43,44,31,34,35,2d,6e,46,a0
G&D Sm@rtCafe Expert 6.0 Non FIPS 144k (T=CL)	3b,8e,80,01,53,43,45,36,30,2d,43,44,31,34,35,2d,6e,46,43
G&D Sm@rtCafe Expert 7.0 CC	3b,f9,96,00,00,80,31,fe,45,53,43,45,37,20,00,00,20,20,27
G&D Sm@rtCafe Expert 7.0 CC (T=CL)	3b,89,80,01,53,43,45,37,20,00,00,20,20,4a
G&D Sm@rtCafe Expert 7.0 FIPS	3b,f9,96,00,00,80,31,fe,45,53,43,45,37,20,03,00,20,46,42
G&D Sm@rtCafe Expert 7.0 FIPS (T=CL)	3b,89,80,01,53,43,45,37,20,03,00,20,46,2f
G&D Sm@rtCafe Expert 7.0 NXP	3b,f9,96,00,00,80,31,fe,45,53,43,45,37,4e,58,50,20,20,41
G&D Sm@rtCafe Expert 7.0 NXP (T=CL)	3b,89,80,01,53,43,45,37,4e,58,50,20,20,2c



Card Name	ATR
Gemalto IDCore 30	3b,7f,96,00,00,80,31,80,65,b0,84,41,3d,f6,12,00,4c,82,90,00
HID Crescendo C700	3b,df,18,ff,81,31,fe,45,80,59,01,80,48,49,44,43,37,30,30,73,00,01,1b,33
Infineon Oracle JCOS Ed.1	3b,fd,96,00,00,80,31,fe,45,53,4c,4a,35,32,47,78,78,79,79,79,7a,52,25
JCOP21 v2.3.1 (Winter AG)	3b,fa,18,00,ff,81,31,fe,45,4a,43,4f,50,32,31,56,32,33,31,65
NXP J2A080 (Winter AG GTN)	3b,fd,18,00,00,81,31,fe,45,06,0b,60,84,10,01,87,6b,01,03,05,04,02,fb
NXP J2A080-J3A080 (TA1=96)	3b,f8,96,00,ff,81,31,fe,45,4a,43,4f,50,76,32,34,31,cd
NXP J2A080-J3A080 (Winter AG)	3b,f8,18,00,ff,81,31,fe,45,4a,43,4f,50,76,32,34,31,43
NXP J2D081	3b,f5,13,00,00,81,31,fe,45,73,74,64,31,30,8f
NXP J3A080	3b,f8,13,00,00,81,31,fe,45,4a,43,4f,50,76,32,34,31,b7
NXP J3D081 (T=CL)	3b,89,80,01,4a,43,4f,50,32,34,32,52,32,4a
NXP JCOP 2.4.2 R3 (Austriacard)	3b,f9,18,00,00,81,31,fe,45,4a,43,4f,50,32,34,32,52,33,a9
NXP JCOP 2.4.2 R3 (exeect Card AG)	3b,f9,18,00,ff,81,31,fe,45,4a,43,4f,50,32,34,32,52,33,56
NXP JCOP 3 SecID P60	3b,dc,18,ff,81,91,fe,1f,c3,80,73,c8,21,13,66,05,03,63,51,00,02,50
Oberthur IDone Cosmo v7.0.1	3b,db,96,00,80,b1,fe,45,1f,83,00,31,c0,64,1a,18,01,00,07,90,00,5a
Oberthur IDone Comso v7.0.2	3b,db,96,00,80,b1,fe,45,1f,83,00,31,c0,64,1f,18,01,00,01,90,00,59
QSCD on JCOP 4 P71	3b,db,18,ff,81,91,fe,1f,c3,06,09,2b,06,01,04,01,e9,10,05,04,d0
RDW ABR kaart	3b,fa,18,00,00,81,31,fe,45,06,08,2a,84,10,01,87,6e,08,08,b1
Rijkspas	3b,fa,18,00,00,81,31,fe,45,06,08,2a,84,10,01,87,6e,08,05,bc
Rijkspas 2	3b,fa,18,00,00,81,31,fe,45,06,08,2a,84,10,01,87,6e,08,07,be
SafeSign Default QSCD	3b,db,18,ff,81,91,fe,1f,c3,06,09,2b,06,01,04,01,e9,10,05,03,d7
StarSign Crypto USB-Token S	3b,f9,96,00,00,81,31,fe,45,53,43,45,37,20,0e,00,20,20,28
UZI-pas 2	3b,fd,18,00,ff,81,31,fe,45,43,49,42,47,55,5a,49,4a,32,41,30,38,31,58
UZI-pas 3	3b,dc,18,ff,81,91,fe,1f,c3,06,0a,2b,06,01,04,01,e9,10,05,02,03,d1
UZI-pas 4	3b,dc,18,ff,81,91,fe,1f,c3,06,0a,2b,06,01,04,01,e9,10,05,02,04,d6



8 Supported Smart Card Readers

SafeSign IC Minidriver version 3.7 provides support for PCSC 2.0 Class 1 readers.

In principle, SafeSign IC supports PC/SC v1.0 compliant smart card readers that supply a current of at least 60mA.

AET recommends that customers make a careful selection of the smart card reader to use, as there are many smart card readers on the market, with such restrictions as 'buggy' PC/SC drivers (especially older smart card reader models), not enough power supply for cryptographic cards (which require a minimum of 60mA) and faulty T=0 or T=1 protocol implementation. These reader problems are beyond the control of smart cards and SafeSign IC.

The following table lists the specific readers that have been tested with SafeSign IC Minidriver version 3.7:

Smart Card Reader Manufacturer and Model	Class
HID Global OMNIKEY 3121 Smart Card Reader Copyright© 2019	1

Note that smart card readers that have been tested or have been working at a given time with a previous SafeSign IC Minidriver versions, may not (still) work or be supported in any or all versions of SafeSign IC Minidriver version 3.7.



9 Supported Applications

SafeSign IC Minidriver version 3.7 has been tested in accordance with AET’s Quality Assurance procedures and the SafeSign IC Minidriver test plan. This includes testing of a number of defined and representative applications to verify a correct functioning of the SafeSign IC components and Libraries.

The following applications have been tested with SafeSign IC Minidriver version 3.7.1.0:

Application	Version	Purpose
Token Administration Utility	3.8.26.1	PKCS #11 token management functions
Mozilla Firefox	95.0	Authentication to a secure web site
Mozilla Thunderbird	91.4.0	Signing and decrypting e-mail messages
Internet Explorer	21H1	Certificate enrollment with key pair generation; Authentication to a secure web site
Microsoft Edge	96.0.1054.43	Authentication to a secure web site
Microsoft Outlook	2016 / 2019 / 2021	Signing and decrypting e-mail messages
Adobe Reader DC	2021.007.20099	Digitally signing a document
Microsoft Word	2016 / 2019 / 2021	Digitally signing a document
LibreOffice	7.2.4.1	
Windows Smart Card Logon	-	Log on to a local Windows client system
Terminal Server Logon	-	Log on to a Windows Terminal Server

- Note that PKCS #11 applications need the PKCS #11 Library to be loaded / installed as a security module. The SafeSign IC PKCS #11 Library (called ‘aetpkss1.dll’) can be found in the system directory.
- Note that (Microsoft) applications do not normally require any configuration, i.e. you do not need to select or install the SafeSign IC card Minidriver.

9.1 Token Administration Utility

With the SafeSign IC Token Administration Utility, you can perform (local) smart card related operations, such as changing the PIN for your smart card or token.

The features available in the Token Administration Utility, can be modified in the Windows registry. The features to be enabled (1) or disabled (0) are located in ‘Actions’.

Refer to the Administrator’s Guide for more details.



9.2 Mozilla Firefox

With SafeSign IC Minidriver installed, you can perform secure web authentication with a SafeSign IC Token.

- Note that as of Firefox 90, you no longer need to install the SafeSign PKCS #11 Library as a security module in Firefox. Doing so, may result in your PIN being asked twice.

9.3 Mozilla Thunderbird

With the SafeSign PKCS #11 Library installed as a security module in Thunderbird, you can send and receive signed and/or encrypted message with a SafeSign IC token.

To verify whether the SafeSign PKCS #11 Library is installed as a security module in Thunderbird, go to Preferences -> Advanced -> Certificates (tab) -> Security Devices (button).

- Note that there is an error in Thunderbird version 91 where decrypting encrypted messages fails, see Known Issues section 5.1. Until Thunderbird fixes the issue, it is recommended to install the SafeSign PKCS#11 library as S/MIME security module.

9.4 Internet Explorer

With SafeSign IC Minidriver installed, you can perform certificate enrollment (i.e. Certificate Services web enrollment for version 2 templates) and secure web authentication in Internet Explorer.

9.5 Microsoft Edge

With SafeSign IC Minidriver installed, you can perform secure web authentication in Microsoft Edge.

9.6 Microsoft Outlook

With SafeSign IC Minidriver installed, you can send and receive signed and/or encrypted messages with a SafeSign IC token.

9.7 Adobe Reader DC

With SafeSign IC Minidriver installed, you can sign documents with a SafeSign IC token.

9.8 Microsoft Word

With SafeSign IC Minidriver installed, you can sign documents with a SafeSign IC token.



9.9 LibreOffice

With SafeSign IC Minidriver installed, you can sign documents with a SafeSign IC token.

9.10 Windows Smart Card Logon

With SafeSign IC Minidriver installed, you can use your SafeSign IC token to log on to a local Windows client machine. This client should be part of a Windows Server domain.

9.11 Terminal Server Logon

With SafeSign IC Minidriver installed, you can use your SafeSign IC token to log on to a remote Windows Terminal Server.



10 Supported Languages

The following languages are supported in SafeSign IC Minidriver version 3.7 (Token Administration Utility):

- Basque (Basque);
- Catalan (Catalan);
- Chinese (Simplified, China);
- Chinese (Traditional, Hong Kong SAR; Traditional, Taiwan);
- Croatian (Croatia);
- Czech (Czechia);
- Dutch (Netherlands);
- English (United States);
- Finnish (Finland);
- French (France);
- German (Germany);
- Hungarian (Hungary);
- Italian (Italy);
- Italian (Switzerland);
- Japanese (Japan);
- Korean (Korea);
- Lithuanian (Lithuania);
- Portuguese (Portugal);
- Portuguese (Brazil);
- Russian (Russia);
- Serbian (Cyrillic, Serbia)
- Serbian (Latin, Serbia);
- Spanish (Spain);
- Thai (Thailand);
- Turkish (Turkey);
- Ukrainian (Ukraine).



10.1 Installation language files and codes

When installing the SafeSign IC Minidriver .msi file, you may apply a transform for the installation language (as described in section 3.4).

For example, to install SafeSign IC Minidriver version 3.7 in Portuguese (Brazil):

```
msiexec /I "SafeSign IC MiniDriver 3.7.1.0-AET.000 64-bits.msi" TRANSFORMS=pt-PT.mst.
```

- Note that WiX does not support all languages, hence the SafeSign IC Installer is not available in the following languages: Italian (Swiss), Lithuanian and Ukranian.

The table below lists the Windows language code identifiers and corresponding transform files:

Language	File
Catalan	ca-ES.mst
Chinese (Simplified characters)	zh-CN.mst
Chinese (Traditional characters)	zh-TW.mst
Croatian	hr-HR.mst
Czech	cs-CZ.mst
Dutch	nl-NL.mst
Finnish	fi-FI.mst
French (France)	fr-FR.mst
German	de-DE.mst
Hungarian	hu-HU.mst
Italian	it-IT.mst
Japanese	ja-JA.mst
Korean	ko-KO.mst
Portuguese (Portugal)	pt-PT.mst
Portuguese (Brazil)	pt-PT.mst
Russian	ru-RU.mst
Serbian (Latin)	sr-latn-cs.mst
Serbian (Cyrillic)	sr-cyrl-cs.mst
Spanish	es-ES.mst
Thai	th-TH.mst
Turkish	tr-TR.mst